



I-O 3235 & I-O 3235F

Getting Started Guide

Installation Instructions

The following steps will guide you through the installation of the I-O 3235/3235F DIMM or CompactFlash into a LaserJet printer.

Please refer to your LaserJet printer user's guide for specific steps on installing optional DIMMs or CompactFlash cards.

1. Perform a self-test of the printer. Then power off the printer.
2. Open the LaserJet's access door or remove the formatter board.
3. Install the DIMM or CompactFlash:
 - For DIMMs, hold the DIMM by the edges (don't touch the edge connector) and insert the DIMM into an available slot. Make sure that the retaining clips on each side are securely locked in place.
 - For CompactFlash cards, hold the Compact Flash card by its edges and line up the grooves in the side of the card with the tabs in a CompactFlash slot. Slide the CompactFlash into place.
 - **Caution:** Do not put the DIMM or CompactFlash in a slot reserved for printer system firmware.
4. Close the access door or re-install the printer's formatter board.
5. Power on the printer. Print a Printer Configuration Page or Menu Map.

If the DIMM or CompactFlash is properly installed, the Configuration Page will show the DIMM or CompactFlash as an installed "Personality" on the Configuration Page. On the Menu Map, you will find menu options for the I-O IPDS and SCS customization options. The printer's front panel will also show menus for I-O's IPDS and SCS customization options.

6. Set the following LaserJet printer options:
 - "Default Personality" as "Auto".
 - I/O time out value to 30 (this is not on the I-O IPDS or SCS menu)
7. After completing these steps, you will need to complete additional configuration of the LaserJet printer and IBM host by following the detailed steps outlined in the I-O 3235 IPDS or SCS User's Guides.

©2005 I-O Corporation. I-O® is a registered trademark of I-O Corporation.
All other trade names or product names referenced are trademarks or registered trademarks of their respective companies.

HPDIMM-QMAN01-102 8/05
* 62.044 *