


## Update Firmware

- Open Your PCoIP Management Console
- Make sure you group your device, it will make the process easier
- Now navigate to the device like shown below



## Import Firmware


- Now you must import the new firmware
- To do this select the import firmware to the left (Red arrow shown above).
- Now save the 4.1.2 firmware file attached in the email somewhere accessible like your desktop
- Now browse for it as shown below and then select the import now button






## Update Device firmware

-Now click the Update Device firmware link to the left as shown below (red arrow)



-Now select the firmware you to choice to update to and click the update device link to the right of the firmware version as shown below.



-Now select a group of devices to update

-Then schedule an update as shown below.



P: 800-871-9998  
W: [www.iocorp.com](http://www.iocorp.com)  
E: [support@iocorp.com](mailto:support@iocorp.com)





**Update Devices**  
Devices must be restarted to use the new firmware version. The checkboxes below can be used to automatically restart devices after a successful update. When checked, Zero Client targets will be restarted immediately while host targets will restart when the host operating system is shutdown and restarted.

**Selected Firmware Version**  
Filename: `tera2_4-1-2_r4_1_2@14565.all`  
Device Family: Tera2  
Version: 4.1.2  
File Description:

**Begin updating targets at:**  
Updates scheduled in the past will begin immediately.  
2013-10-31 09:43

**Device restart options:**  
 Immediately restart Zero Clients when update is complete  
 Schedule deferred restart on hosts when update is complete

Select	Name	Type	Group	IP Address	Version	Device Family
<input type="checkbox"/>	pcoip-host-0030040e6340	Host	IO Corp Hosts		4.0.3	Tera2
<input type="checkbox"/>	pcoip-portal-0030040e2d74	Zero Client	IO Corp	10.1.1.164	4.0.2	Tera2

### View status

- This will let you check the current update and past ones to make sure they completed okay
- Select the link to the left view status to check current and past upgrades



**P: 800-871-9998**  
**W: [www.iocorp.com](http://www.iocorp.com)**  
**E: [support@iocorp.com](mailto:support@iocorp.com)**

